Split Core Current Transformers(outdoor use)

SCTK667D Series

SCTK667D series retro-fit (split-core) current transformer has been specially designed to facilitate their installation in new or already existing net works. They may be installed without opening any cable or bus-bar circuit. An internal precision resistor across the secondary winding of the CT provides a low safe voltage output. It can save time and the installation costs.


Features

- Outdoor use, resisting wind, rain and UV fading,IP65, Acquisition voltage signal in the field
- Wide inner window, allowing clamping of big cables or bus-bars
- Wide range of sizes to accommodate all the existing installations

Applications

- Current measurement, monitoring and protection for electrical wiring and equipment.
- Current and power measurement for electric motors, lighting, air compressor,heating and ventilation system, air-condition equipment and automation – control system.
- Current, power and energy monitoring device.

Circuit connection diagram




Designation

SC	T.K	
		Rateo ID dir
		Produ Split
		Split Curre Comr

Rated Input/Output ID dimension Product model Split core type Current Transformer Company Name in short





Technique Index

Electrical Parameter			Mechanical Pa	arameter		
Frequency	50-60Hz		Case	PC+ABS/UL94-V0		
Rated Input	50A-2000A		Bobbin	PBT		
Measuring range	1%In-130%In		Core	Permalloy		
Rated Output	1A/5A		Internal structure	Ероху		
Ratio	≤± 0.2%		Construction	Tie		
Phase angle	≤ ±10min		Operating Temp	−40°C~+85°C		
Dielectric strength	3.0KV/1mA/1min		Operating Humidity	≤96%		
Insulation Resistance	DC500V/100MΩ min		Output Connection	Terminal or UL14AWG Wire 1.5m		

Type Selection

- /	Rated Input (A)	Output (A)	Accuracy	Dimensions(mm)				
P/N				Ø	Α	В	с	
SCTK667D-025	50-400A	1A/5A	0.5、1.0、3.0	25	173	105	56	
SCTK667D-032	100-630A	1A/5A	0.5、1.0、3.0	32	206	112	56	
SCTK667D-045	100-1000A	1A/5A	0.2、0.5、1.0	45	193	125	56	
SCTK667D-055	100-1200A	1A/5A	0.2、0.5、1.0	55	180	135	56	
SCTK667D-065	100-1500A	1A/5A	0.2、0.5、1.0	65	203	145	56	
SCTK667D-080	200-2000A	1A/5A	0.2、0.5、1.0	80	228	160	56	
SCTK667D-100	500-3000A	1A/5A	0.2、0.5、1.0	100	248	180	56	

ShaanXi Shinhom Enterprise Co.,Ltd

Tel: +86-029-87851838 **Fax:** +86-029-87851840

Web: Http://www.shinhom.com Mail: sales@shinhom.com.cn

